BF-20 Relay Box



Description

- Combined with BF -660C /BF-880/NBDE Series Reader to control single door.
- Split system, more security for door access control.
- Compact size and easy to make installation.
- One relay output and two inputs for door sensor and Exit button.
- RS-485 communication.
- Watch dog inside.
- Power : DC-9 ~ 30V.

Connection

- VIN : Power +
 GND : Power -
- Door sensor connector: S1, S2
 Exit button connector: B1, B2
 RS-485 connector: 485+, 485-
- Relay output: COM: (relay capacity: 1A /125VAC , 1A /30VDC) , NO, NC